

# ACT-311 Single-Channel Diversity Receiver



## Introduction

The innovative ACT 3 Series wireless microphone systems are a culmination of years of extensive design and manufacturing experience. No wiring and adjustment required as PCB, LCD and front panel are integrated.

EIA standard 19" rack-mountable metal chassis is used instead of cheap plastics. Featuring backlit LCD instead LED display for ease of use and professional appearance. PLL-synthesized technology for RF stability and matched with rugged ACT-30H & ACT-30T transmitters. Design and made in Taiwan. Advanced features and functions make it ideal for professional applications with affordable prices.

## Key Features

- EIA standard 1/2U metal receiver.
- Receiver provides bias for booster where MIPRO antenna systems can be added for extended receiving range and stability.
- Backlit LCD displays group, channel, frequency, RF level, antenna selection, AF level, battery level indicator, interference warning indicator, and panel lock indicator.
- A lit green light indicates a working mode when receiver detects an incoming signal or buttons touched. Light dims automatically when receiver is idle for about 10 seconds.
- Balanced XLR / unbalanced 1/4 " audio output jack, output level switch and DC input are on the rear panel. One mixed-output switch is available for dual-channel receivers.
- High efficiency and low spurious PLL circuitry with Auto Scan function. Each receiver is presets with 11 groups, Groups 1~6, 7~10 have 8 & 16 compatible channels respectively. Up to 8 channels in group 11 can be saved and recalled within 961 user-defined frequencies. A total of 112 preset channels per band.
- World's first ACT™ function provides precise and rapid frequency sync to the transmitters.
- Advanced diversity technology for optimum reception range and reduces signal dropouts and the "PiloTone & NoiseLock" dual-squelch circuits prevent noise interference.
- Adjustable 'SQ' for higher sensitivity to increase receiving distance and lower sensitivity to reduce interference.
- Industry's only RF interference warning indicator for ideal SQ level adjustment.
- DC input socket accepts 12~15V power supply.



## Transmitters

<b>ACT-30H</b>	Handheld Transmitter
<b>ACT-30T</b>	Bodypack Transmitter

## Accessories

<b>AD-707a</b>	UHF Wideband 4-Channel Antenna Divider
<b>AD-708</b>	UHF Wideband 4-Channel Auto Gain-Control Antenna Divider
<b>AT-70</b>	UHF Ground Plane Antenna
<b>AT-70W   AT-70Wa</b>	Wideband Transmitting & Receiving Omni-directional Antenna
<b>AT-90W   AT-90Wa</b>	Wideband Transmitting & Receiving Log Antenna
<b>AT-100   AT-100a</b>	Wideband Circularly Polarized Antenna
<b>FB-71</b>	Rack Mount Kit
<b>FBC-71</b>	Rear-to-Front Cables

## Technical Specifications

Channel	Single
Chassis	EIA-Standard 19" 1/2U
Receiving Mode	Diversity
Frequency Range	UHF 480~934MHz
Antenna	Rear Panel. Detachable.
Preset Channels	112 preset channels. Group 1-6: 8 compatible channels in each group. Group 7-10: 16 compatible channels in each group. Group 11: Up to 8 channels can be saved & recalled. 961 user-defined frequencies in group 11.
Oscillation Mode	PLL Synthesized, Frequency Stability ± 0.005% (-10~+60 °C)
Sensitivity	10dBμV, at S/N>80dB
S/N Ratio	> 106dB(A)
T.H.D.	<0.5% @ 1kHz
Frequency Response	50Hz~18kHz, with high pass filter.
Squelch	"PiloTone & NoiseLock" dual-squelch circuit.
Audio Output Adjustment	Output level accurately pre-adjusted to equal to the microphone capsule sensitivity.
Maximum Output Level	2-level Switch: Line & Mic
Power Supply	External AC Adapter, 12~15V DC, 1A
Dimensions	210(W)× 44(H)× 180(D)mm / 8.3(W)× 1.7(H)× 7.1(D)"
Weight	Approx. 0.8kg / 1.8lbs



## MIPRO Electronics Co., Ltd

Headquarters: 814 Pei-kang Road, Chiayi, 60096, Taiwan  
Tel: +886.5.238.0809 | Fax: +886.5.238.0803  
www.mipro.com.tw | mipro@mipro.com.tw